## **SPECIFICATION**

### For

## SWITCHING POWER SUPPLY

## M/N: MPD-810H-1

| Revision Hi | story         |  |  |  |  |
|-------------|---------------|--|--|--|--|
| Version     | Revise Date   | Change Items   |  |  |  |
| Rev. 01     | Apr. 22. 2008 | Update mechanical drawing.                                 |  |  |  |
| Rev. 02     | Jul. 26. 2010 | Updating minimum load of +5V is 0.5A.                      |  |  |  |
| Rev. 03     | Mar. 28. 2011 | Updated the safety approvals status.                       |  |  |  |
| Rev. 04     | Jan. 11. 2018 | <ol> <li>Changed form.</li> <li>Added EN 55032.</li> </ol> |  |  |  |
| Rev. 05     | Dec. 20. 2018 | Added output current to output field.                      |  |  |  |
|             |               |  |  |  |  |
|             |               |  |  |  |  |



### 120W DC / DC





#### **FEATURES**

✓ MPD-810H-1 is 120 watts with forced air cooling, 85 watts with convection cooling, 10-30 VDC input, five outputs switching power supply, it is designed for use in General Purpose.



| Models & Ratings |                          |                |        |              |                  |              |
|------------------|--------------------------|----------------|--------|--------------|------------------|--------------|
| Model Number     | Wattage<br>(Rated / Max) | Output Voltage |        | Min. Current | Rated<br>Current | Max. Current |
|                  | 85 W / 120 W             | V1             | +5 V   | 0.5 A        | 2.5 A            | 5.0 A        |
|                  |                          | V2             | +12 V  | 0 A          | 5 A              | 7.0 A        |
| MPD-810H-1       |                          | V3             | -12 V  | 0 A          | 0.5 A            | 1.0 A        |
|                  |                          | V4             | +3.3 V | 0 A          | 2.5 A            | 5.0 A        |
|                  |                          | V5             | +5Vsb  | 0 A          | 0.75 A           | -            |

Total Output Power: 120 watts with forced air cooling, 85 watts with convection cooling.

Note:

1. At the factory, the +5V output is set between 5.08V to 5.13V and all output at 60% rated load; the other outputs are checked to be within the accuracy range. The maximum total combined output power on the +3.3V and +5V rails is 70W. The maximum load cannot exceed 120W.

| Summary               |  |  |         |       |  |  |
|-----------------------|--|--|---------|-------|--|--|
| Characteristic        | Minimum  | Typical  | Maximum | Units | Notes & Conditions   |  |
| Input Range           | 10   | 12 / 24  | 30      | VDC   |  |  |
| Efficiency            |  |  | >70     | %     | While measuring at nominal line and rated.                                 |  |
| Operation Temperature | 0  |  | +50     | °C    | Output power is 120 watts forced air cooling, 85 watts convection cooling. |  |
| Dimensions            | 141.6 (L) x 83.8 (W) x 38.0 (H) mm, Tolerance +/- 0.4mm. |  |         |       |  |  |
| EMC                   | FCC docket 20<br>IEC 61000-4-2                           | FCC docket 20780 curve " B" ,EN 55022 / EN 55032 (Radiation Class B),<br>IEC 61000-4-2, IEC 61000-4-3, IEC 61000-4-4 |         |       |  |  |
| Safety Approvals      | UL 60950-1 First Edition, CAN/CSA C22.2 No.60950-1       |  |         |       |  |  |



| Input          | Ì       |         |         |       |                    |
|----------------|---------|---------|---------|-------|--------------------|
| Characteristic | Minimum | Typical | Maximum | Units | Notes & Conditions |
| Input Voltage  | 10      | 12 / 24 | 30      | VDC   |                    |
| Input Current  |         |         | 18      | А     | At 10 VDC Input.   |
| Inrush Current |         |         | 30      | A     | At 10 VDC Input.   |

| Output               | Ì                                 |  |               |                 |   |  |
|----------------------|-----------------------------------|--|---------------|-----------------|---|--|
| Characteristic       | Minimum                           | Typical  | Maximum       | Units           | Notes & Conditions  |  |
|                      |                                   | +5 V   |               |                 |   |  |
|                      |                                   | +12 V  |               | 1               |   |  |
| Output Voltage       |                                   | -12 V  |               | DC              |   |  |
|                      |                                   | +3.3 V   |               |                 |   |  |
|                      |                                   | +5Vsb  |               |                 |   |  |
|                      |                                   | 2.5  | 5.0           |                 |   |  |
|                      |                                   | 5  | 7.0           |                 |   |  |
| Output Current       |                                   | 0.5  | 1.0           | А               |   |  |
|                      |                                   | 2.5  | 5.0           |                 |   |  |
|                      |                                   | 0.75   | -             |                 |   |  |
|                      | 4.95                              |  | 5.15          |                 |   |  |
|                      | 11.25                             |  | 12.75         |                 |   |  |
| Initial Set Accuracy | -11.75                            |  | -13.1         | VDC             |   |  |
|                      | 3.0                               |  | 3.5           |                 |   |  |
|                      | 4.8                               |  | 5.2           |                 |   |  |
| Minimum Load         |                                   | 0.5  |               | A               | At Output Voltage +5V   |  |
|                      |                                   | 0  |               |                 | At Output Voltage +12 V, -12 V, +3.3 V, +5Vsb   |  |
| Line Regulation      |                                   | $\begin{array}{c} \pm 2.5^{(V1)} \\ \pm 2.5^{(V2)} \\ \pm 2.5^{(V3)} \\ \pm 2.5^{(V4)} \\ \pm 2.5^{(V5)} \end{array}$  |               | %               | Less than $\pm 2.5\%$ at rated load with $\pm 10\%$ changing in input voltage.  |  |
| Load Regulation      |                                   | $\begin{array}{c} \pm 2.0^{(\vee 1)} \\ \pm 5.0^{(\vee 2)} \\ \pm 5.0^{(\vee 3)} \\ \pm 5.0^{(\vee 4))} \end{array}$   |               | %               | While the measuring is done by changing the measured output loading $\pm 40\%$ from 60% rated load , and keep other output is at 60% rated load.            |  |
| Ripple & Noise       |                                   | 100 <sup>(V1)</sup><br>120 <sup>(V2)</sup><br>200 <sup>(V3)</sup><br>100 <sup>(V4)</sup><br>120 <sup>(V5)</sup>  |               | mV              | At rated load and nominal input, which is measured by a 20MHz bandwidth limited oscilloscope and the each output is connected with a $0.47\mu$ F capacitor. |  |
| Protection           | The power sur<br>return to norm   | The power supply will generate the hiccup mode to protect itself against short circuit or over load condition, and will return to normal after wrong condition is removed. |               |                 |   |  |
| Power On / Off       | The power su                      | oply will start-up   | when the powe | r On/Off pin be | connected to secondary GND.   |  |
| Power good signal    | The power is t<br>are within regu | The power is turned on, the power good signal will go high between 100ms to 500ms after all output DC voltage are within regulation limits.                                |               |                 |   |  |
| Power fail signal    | The power fail                    | The power fail signal will go low at least 1ms before any of the output voltages fall below the regulation limits.   |               |                 |   |  |



## Environmental

| Characteristic        | Minimum | Typical | Maximum | Units | Notes & Conditions   |
|-----------------------|---------|---------|---------|-------|--|
| Operation Temperature | 0       |         | +50     | °C    | Output power is 120 watts forced air cooling, 85 watts convection cooling. |
| Storage Temperature   | -40     |         | +70     | °C    |  |
| Relative Humidity     | 10      |         | 90      | %RH   | Non-condensing.  |
| Cooling               | 18.0    |         |         | CFM   | Forced-cooled > 85W  |
| Operating Altitude    | 0       |         | 10000   | Feet  |  |

#### **EMC: Emissions**

| Phenomenon | Standard                              | Class | Notes & Conditions |
|------------|---------------------------------------|-------|--------------------|
| Conducted  | FCC docket 20780, EN 55022 / EN 55032 | В     |                    |
| Radiated   | FCC docket 20780, EN 55022/ EN 55032  | В     |                    |

#### **EMC:** Immunity

| Phenomenon | Standard      | Level | Notes & Conditions |
|------------|---------------|-------|--------------------|
| ESD        | IEC 61000-4-2 | 3     | ±8KV air discharge |
| Radiated   | IEC 61000-4-3 | 3     | 3V/m               |
| EFT        | IEC 61000-4-4 | 3     | 2KV                |

### Safety Approvals

| Safety Agency | Safety Standard                                    | Notes & Conditions |
|---------------|--|--------------------|
| UL/cUL        | UL 60950-1 First Edition, CAN/CSA C22.2 No.60950-1 | Approved.          |



#### **Mechanical Details**

SIZE : 141.6(L) x 83.8(W) x 38.0(H)mm, Tolerance specified is ±0.4mm.



